

# TX8202

8 Channel Stereo Mic/Line  
Mixer with Direct Outputs

## Description

The TX8202 is a high performance 8 channel stereo mixer suitable for desk or rack mounting.

## Inputs and Outputs

The TX8202 has four active balanced mic/line inputs and four stereo line inputs. Each channel features recessed treble, bass and pan controls. Mic/Line level can be adjusted per channel via a dip switch. All mic and line input connections are via 3 pin XLR female sockets, and all stereo line input connections are via dual female RCA sockets. Both the Left and Right outputs are balanced and feature 3 pin male XLR sockets. A stereo tape output using dual female RCA sockets is also provided. A 1/4" stereo headphone socket is included on the front panel. The rear panel includes a terminal block for activation of the optional Tone Generator. The first four channels feature a line level direct output which can be used to feed additional amplifiers, mixers or recording devices. An internal jumper allows the first four inputs to be removed from the master left/right outputs whilst still retaining their direct output function.

## Controls and Metering

Front panel controls include Master Left and Right Outputs plus individual channel level controls. Each channel also features a recessed, screwdriver adjustable treble, bass and pan control. A four position dip switch (mic/line, phantom power, routing) is provided for the first four channels. A 7 segment LED meter is provided for both the Left and Right Outputs. A power "on" orange LED is part of the LED meter. An optional remote master VCA is available for remote master volume control.

## VCA Control

The optional VCA control module (AMVCA) allows the master volume to be remotely controlled. External VCA control would normally be via potentiometer connected to a two wire rear panel barrier strip.

## Muting

Muting is standard on the unit for channels one and two. Both channels have equal priority and will mute channels 3-8 when signal is present. The muting function can be disabled by moving an internal jumper.

## Tone Generators

Bell, Pre-Announce Chime, Evacuate and Alert are included in the unit. Each tone can be activated by a simple contact closure using the rear panel terminal block.

## Phantom Power

Phantom Power (15V DC) is available on all mic inputs and can be disabled if required via a dip switch.

## Accessories

**AM Tone1** – This module provides simple 4 tone generation for the MX series mixers. Tones available are alert, evac, pre-announce, and bell.

**AM Tone** – This module allows for high quality pre-announce, bell, alert, evac, tones, to be generated on board the MX series mixers.

**AM VCA** – This module allows for a remote master volume control to be used with the MX series mixers.



<b>Frequency Response</b>	50Hz - 15kHz ( $\pm$ 3dB)
<b>Total Harmonic Distortion</b>	Less than 0.1% @ 1kHz
<b>Signal To Noise Ratio</b>	-74dBV (all channels at centre position)
<b>Tone Controls</b>	Bass @ 100Hz - Boost +12dB, Cut -12dB; Treble @ 10kHz - Boost +10dB, Cut -10dB
<b>Inputs</b>	4 active balanced mic/line inputs with 3 pin XLR female sockets (200 - 600 Ohms) Maximum Input Level is 500mV; 4 Stereo Line inputs with dual female RCAs (47K Ohms) Maximum Input Level is 1.5V
<b>Input Sensitivity</b>	Mic: 1mV @ 200 Ohms; Line 1-4: 150mV - 1V @ 47K Ohms; Line 5-8: 125mV @ 47K Ohms
<b>Phantom Power</b>	15V DC on all mic channels (switchable)
<b>Outputs</b>	Left and Right Master Outputs, 3 pin XLR male sockets. (1.5V @ 600 Ohms.) Maximum Output Level: +20dB; Stereo Headphone Output, 1/4" stereo socket. (3.5V @ 600 Ohms) Stereo Tape Output, dual female RCA connectors. (400mV @ 10K Ohms) Four direct line level outputs (600mV @ 10K Ohms)
<b>Controls</b>	Level Control per channel, Recessed Treble, Bass and Pan Controls per channel, Left and Right Master Level Controls
<b>Indicators</b>	Power "on" orange LED, 7 segment LED meters for both L and R outputs
<b>Power Source</b>	AC: 240V - 50Hz or 110V - 60Hz (special order) 3 pin IEC connector
<b>Power Consumption</b>	7 Watts
<b>Dimensions/Weight</b>	44mm H x 482mm W x 250mm D (Chassis dimensions only). 4kg

#### ARCHITECTURAL AND ENGINEERING SPECIFICATIONS

The mixer shall have 4 balanced mic/line inputs and 4 stereo line inputs. The mic/line channels shall be balanced and feature 3 pin female XLR sockets. The stereo line channels shall have dual female RCA sockets. Each channel shall include tamper resistant treble, bass, and pan controls. The first four channels feature a line level direct output which can be used to feed additional amplifiers, mixers or recording devices. An internal jumper shall allow the first four inputs to be removed from the master left/right outputs whilst still retaining their direct output function. The equalisation per channel shall provide 12dB cut or boost at 100Hz and 10dB cut or boost at 10kHz. The master section shall include individual level controls for both the Left and Right outputs and shall also include two 7 segment output level LED meters. The master outputs shall be balanced 3 pin XLR male sockets, and dual RCA female sockets for the stereo tape output. A 1/4" stereo headphone socket shall be included for monitoring. The mixer shall include on board muting card, as well as a option for 4 tone generator modules and remote master VCA control.

The mixer shall be of high quality, suitable for both live and commercial applications. It should have ample headroom and a frequency response of no less than 50Hz - 15kHz ( $\pm$ 3dB). Total Harmonic distortion shall be no more than 0.1% at 1kHz. The S/N ratio shall be -74dBV or better. Phantom Power of no less than 15V DC shall be available on all microphone inputs. An internal switch to disable the phantom power on any of the mic/line channels shall also be included. The unit shall be packaged in a rugged 1 RU metal chassis suitable for desk or rack mounting.

The mixer shall be an Australian Monitor Installation Series model TX8202.



Engineered and Distributed by AUDIO TELEX COMMUNICATIONS PTY LTD (ABN 78 001 345 482), 149 Beaconsfield Street, Silverwater, Sydney, NSW, 2128

NSW Tel: (02) 9647 1411 Fax: (02) 9648 3698 VIC Tel: (03) 9890 7477 Fax: (03) 9890 7977 QLD Tel: (07) 3852 1312 Fax: (07) 3252 1237 WA Tel: (08) 9228 4222 Fax: (08) 9228 4233

Tas Tel: (03) 6228 6373 Fax: (03) 6278 1063 SA Tel: (08) 8352 4444 Export Enquiries: export@audiotelex.com.au Website: [www.australianmonitor.com.au](http://www.australianmonitor.com.au)